

Maintenance Schedule Of Breathing Air Units

(Types of Maintenance Kits can be found below)



Quality. Our DNA

Incl.	Maintenance kit (MK):	a1	ab1	a1	abc1	a1	ab1	a1	abc1	abc1
in	Maintenance and testing works depending on time**:	yearly	2 years	3 years	4 years	5 years	6 years	7 years	8 years	16 years
MK:	Maintenance and testing works depending on operating hours**:	500hrs	1,000hrs	1,500hrs	2,000hrs	2,500hrs	3,000hrs	3,500hrs	4,000hrs	8,000hrs
*	ACD – to be maintained and checked (separate kit available!)	X	X	X	X	X	x	х	X	X
	Anti vibration elements – function to be checked (exchange if damaged)	X	X	Х	Х	X	х	х		
*	Anti vibration elements – to be exchanged								X	X
	Cylinders, piston and piston rings – to be checked for wearing				Х				X	X
*	Cylinders, piston and piston rings – to be exchanged (exchange in combination only)	As required								
	Electrical motor – to be lubricated (if lubricating nipples available)	X	X	Х	х	Х	X	X	X	X
	Electrical terminal clamps – to be checked for strength	X	X	х	х	х	x	x	x	X
	Emergency button – function to be checked (if mounted)	X	X	х	х	х	x	x	x	X
	Fan blades – to be checked	X	X	х	х	х	x	x	x	x
*	Fan blades – to be exchanged (if possible)	Every 10 years								
*	Filter cartridge – to be exchanged	As required / According to saturation								
*	Final separator filter cartridge – to be exchanged	X	X	X	X	X	X	X	X	X
	Fittings to be fixed according to torque load	Х	X	X	Х	х	X	X	X	X
	Functional testing, final inspection, test run	Х	x	х	х	х	x	x	x	x
a1	Intake filter – to be exchanged	Х	x	х	х	х	x	x	x	x
	Intermediate pressures (all stages) and oil pressure - to be checked	Х	x	х	х	х	x	x	x	x
	Leak test and general visual inspection of unit	X	X	х	х	х	x	x	x	x
*	Oil (mineral) – to be exchanged	X	X	X	X	X	X	X	X	X
*	Oil (synthetic) – to be exchanged		X		X		X		X	X
a1	Oil filter cartridge – to be exchanged	Х	X	х	X	х	X	X	X	X
	Oil injection nozzle – function to be checked and cleaned (exchange if damaged)	X	X	х	х	х	x	x		
*	Oil injection nozzle – to be exchanged								X	X
*	Oxygen sensors – to be exchanged (B- Trox units only)	Х	x	х	х	х	x	х	х	X
	Piston and sleeve assembly – to be checked	X		X		X		X		
b1	Piston and sleeve assembly – to be exchanged		X		Х		x		X	X
	Pressure gauges – to be checked for function and precision	Х	X	х	X	X	x	x	X	X
	Pressure hoses/hoses -to be checked for tightness and damages (exch. if necessary)) Every 6 months								

*Not included in maintenance kit a/b/c. To be ordered separately. Maintenance between 8 years and 16 years / 4,000hrs and 8,000hrs similar to the previous intervals. **Maintenance and testing works according to interval that comes first (time OR operating hours).

Maintenance Kit versions and interval: see last page



Maintenance Schedule Of Breathing Air Units

(Types of Maintenance Kits can be found below)



Quality. Our DNA

Incl.	Maintenance kit (MK)	a1	ab1	a1	abc1	a1	ab1	a1	abc1	abc1
in	Maintenance and testing works depending on time**:	yearly	2 years	3 years	4 years	5 years	6 years	7 years	8 years	16 years
MK	Maintenance and testing works depending on operating hours**:	500hrs	1,000hrs	1,500hrs	2,000hrs	2,500hrs	3,000hrs	3,500hrs	4,000hrs	8,000hrs
*	Pressure hoses / hoses – to be exchanged	Every 6 years								
*	Pressure relief valve - to be checked (order maintenance kit if necessary)	x	X	х	х	х	X	x	Х	X
	Pressure sensors - to be checked (if available)				х				X	X
	Pressure switches and pressure relief valve settings – to be checked	X	X	X	X	X	X	x	X	X
	Pressure vessel – to be checked (according to PED – Pressure Equipment Directive)					X				
*	Pressure vessel - to be exchanged after reaching maximum amount of load cycles	According to PED								
	Pressure vessel, recording of working hrs and load cycles - to be controlled visually	X	X	x	х	х	х	x	X	X
	Reporting, test sticker to be attached	X	X	x	х	х	х	x	X	X
*	Safety valves - to be checked (no tests possible \rightarrow SV have to be exchanged)	X	X	x	х	х	х	x	X	X
a1	Seals and o-rings acc. to maintenance kit – to be exchanged	X	X	x	х	х	х	x	X	X
c1	Seals and o-rings acc. to maintenance kit – to be exchanged				X				X	X
	Separator, drain of condensate collector – to be cleaned and checked for damages	X	Х	x	х	х	х	x	Х	Х
	Suction- and pressure valves - to be checked (all stages)	X		x		х		x		
b1	Suction- and pressure valves – to be exchanged (all stages)		X		х		х		Х	X
	Temperature sensors - to be checked (if available)				х				Х	X
	V-belt - to be checked	x	X	х		х	х	x		
*	V-belt – to be exchanged				X				X	X

*Not included in maintenance kit a/b/c. To be ordered separately. Maintenance between 8 years and 16 years / 4000hrs and 8000hrs similar to the previous intervals.

**Maintenance and testing works according to interval that comes first (time OR operating hours).

Maintenance Kit Versions:

(Diving, Fire Fighting)	Maintenance Interval:	500hrs
(Nitrogen, Argon)	Maintenance Interval:	1.000hrs
(Natural Gas)	Maintenance Interval:	2.000hrs
(Helium; for G-Units with He applications, too)	Maintenance Interval:	1.000hrs
(Industry-Air Applications; others)	Maintenance Interval:	1.000hrs
	(Nitrogen, Argon) (Natural Gas) (Helium; for G-Units with He applications, too)	(Nitrogen, Argon)Maintenance Interval:(Natural Gas)Maintenance Interval:(Helium; for G-Units with He applications, too)Maintenance Interval: